

3.1 Definition of Stability

The term stability refers to the stable working condition of a control system. Every Working system is designed to be stable. In a stable, the response or output is predictable, finite and stable for a given input.

The different definitions of the stability are the following

1. A system is stable, if its output is bounded for any bounded input.
2. A system is asymptotically stable, if in the absence of the input, the output tends towards zero irrespective of initial conditions.
3. A system is stable if for a bounded disturbing input signal the output vanishes ultimately as t approaches infinity.
4. A system is unstable if for a bounded disturbing input signal the output is of infinite amplitude or oscillatory.
5. For a bounded input signal, if the output has constant amplitude oscillations then The system may be stable or unstable under some limited constraints. Such a system is called limitedly stable.
6. If a system output is stable for all variations of its parameters, then the system is called absolutely stable system.
7. If a system output is stable for a limited range of variations of its parameters, then the system is called conditionally stable system

Control Systems - Stability Analysis

In this chapter, let us discuss the stability analysis in the s domain using the RouthHurwitz stability criterion. In this criterion, we require the characteristic equation to find the stability of the closed loop control systems.

Routh-Hurwitz Stability Criterion

Routh-Hurwitz stability criterion is having one necessary condition and one sufficient condition for stability. If any control system doesnt satisfy the necessary condition, then we can say that the control system is unstable. But, if the control system satisfies the necessary condition, then it may or may not be stable. So, the sufficient condition is helpful for knowing whether the control system is stable or not.

Necessary Condition for Routh-Hurwitz Stability

The necessary condition is that the coefficients of the characteristic polynomial should be positive. This implies that all the roots of the characteristic equation should have negative real parts.

Consider the characteristic equation of the order n is -

$$a_n s^n + a_{n-1} s^{n-1} + a_{n-2} s^{n-2} + \dots + a_1 s^1 + a_0 s^0 = 0$$

Note that, there should not be any term missing in the n^{th} order characteristic equation. This means that the n^{th} order characteristic equation should not have any coefficient that is of zero value.

Sufficient Condition for Routh-Hurwitz Stability

The sufficient condition is that all the elements of the first column of the Routh array should have the same sign. This means that all the elements of the first column of the Routh array should be either positive or negative.

Routh Array Method

If all the roots of the characteristic equation exist to the left half of the s plane, then the control system is stable. If at least one root of the characteristic equation exists to the right half of the s plane, then the control system is unstable. So, we have to find the roots of the characteristic equation to know whether the control system is stable or unstable. But, it is difficult to find the roots of the characteristic equation as order increases.

So, to overcome this problem there we have the **Routh array method**. In this method, there is no need to calculate the roots of the characteristic equation. First formulate the Routh table and find the number of the sign changes in the first column of the Routh table. The number of sign changes in the first column of the Routh table gives the number of roots of characteristic equation that exist in the right half of the s plane and the control system is unstable.

Follow this procedure for forming the Routh table.

Fill the first two rows of the Routh array with the coefficients of the characteristic polynomial as mentioned in the table below. Start with the coefficient of s^n and continue

up to the coefficient of s^0 .

Fill the remaining rows of the Routh array with the elements as mentioned in the table below. Continue this process till you get the first column element of row s^0 is a_n . Here, a_n is the coefficient of s^0 in the characteristic polynomial.

Note – If any row elements of the Routh table have some common factor, then you can divide the row elements with that factor for the simplification will be easy.

The following table shows the Routh array of the n^{th} order characteristic polynomial.

$$a_0s^n + a_1s^{n-1} + a_2s^{n-2} + \dots + a_{n-1}s^1 + a_ns^0$$

s^n	a_0	a_2	a_4	a_6
s^{n-1}	a_1	a_3	a_5	a_7
s^{n-2}	$\frac{b_1}{1} = \frac{a_1 a_2 - a_3 a_0}{a}$	$\frac{b_2}{a_1} = \frac{a_1 a_4 - a_5 a_0}{a_1}$	$\frac{b_3}{1} = \frac{a_1 a_6 - a_7 a_0}{a}$
s^{n-3}	$\frac{c_1}{b_1} = \frac{b_1 a_3 - b_2 a_1}{b_1}$	$\frac{c_2}{b_1} = \frac{b_1 a_5 - b_3 a_1}{b_1}$	\vdots			
\vdots	\vdots	\vdots	\vdots			
s^1	\vdots	\vdots				
s^0	a_n					

s^4	1	3	1
s^3	3	2	
s^2	$\frac{(3 \times 3) - (2 \times 1)}{3} = \frac{7}{3}$	$\frac{(3 \times 1) - (0 \times 1)}{3} = \frac{3}{3} = 1$	
s^1	$\frac{(\frac{7}{3} \times 2) - (1 \times 3)}{\frac{7}{3}} = \frac{5}{7}$		
s^0	1		

The first element of any row of the Routh array is zero. All the elements of any row of the Routh array are zero.

Let us now discuss how to overcome the difficulty in these two cases, one by one.

First Element of any row of the Routh array is zero

If any row of the Routh array contains only the first element as zero and at least one of the remaining elements have non-zero value, then replace the first element with a small positive integer, ϵ . And then continue the process of completing the Routh table.

Now, find the number of sign changes in the first column of the Routh table by substituting ϵ tends to zero.

Example

Let us find the stability of the control system having characteristic equation,

$$s^4 + 2s^3 + s^2 + 2s + 1 = 0$$

Step 1 – Verify the necessary condition for the Routh-Hurwitz stability.

All the coefficients of the characteristic polynomial, $s^4 + 2s^3 + s^2 + 2s + 1$ are positive. So, the control system satisfied the necessary condition.

Step 2 – Form the Routh array for the given characteristic polynomial.

s^4	1	1	1
s^3	2	2	1
s^2	1	$\frac{(1 \times 1) - (1 \times 1)}{2} = 0$	$\frac{(1 \times 1) - (0 \times 1)}{2} = 1$
s^1			
s^0			

The row s^3 elements have 2 as the common factor. So, all these elements are divided by 2.

Special case (i) – Only the first element of row s^2 is zero. So, replace it by ϵ and continue the process of completing the Routh table.

s^4	1	1	1
s^3	1	1	
s^2	ϵ	1	
s^1	$\frac{(\epsilon \times 1) - (1 \times 1)}{\epsilon} = \frac{\epsilon - 1}{\epsilon}$		
s^0	1		

Step 3 – Verify the sufficient condition for the Routh-Hurwitz stability. As ϵ

tends to zero, the Routh table becomes like this.

s^4	1	1	1
s^3	1	1	
s^2	0	1	
s^1	$-\infty$		
s^0	1		

There are two sign changes in the first column of Routh table. Hence, the control system is unstable.

All the Elements of any row of the Routh array are zero

In this case, follow these two steps –

Write the auxiliary equation, $A(s)$ of the row, which is just above the row of zeros.

Differentiate the auxiliary equation, $A(s)$ with respect to s . Fill the row of zeros with these coefficients.

Example

$$s^5 + 3s^4 + s^3 + 3s^2 + s + 3 = 0$$

Step 1 – Verify the necessary condition for the Routh-Hurwitz stability.

All the coefficients of the given characteristic polynomial are positive. So, the control system satisfied the necessary condition.

Step 2 – Form the Routh array for the given characteristic polynomial.

s^5	1	1	1
s^4	3	1	3
s^3	1	$\frac{(1 \times 1) - (1 \times 1)}{3} = 0$	$\frac{(1 \times 1) - (1 \times 1)}{3} = 0$
s^2			
s^1			
s^0			

The row s^4 elements have the common factor of 3. So, all these elements are divided by 3.

Special case (ii) – All the elements of row s^3 are zero. So, write the auxiliary equation, A(s) of the row s^4 .

$$A(s) = s^4 + s^2 + 1$$

Differentiate the above equation with respect to s.

$$\frac{dA(s)}{ds} = 4s^3 + 2s$$

Place these coefficients in row s^3 .

s^5	1	1	1
s^4	1	1	1

s^3	4 2	2 1	
-------	-----	-----	--

s^2	2	$\frac{(2 \times 1) - (1 \times 1)}{0.5} = 0.5$	2	$\frac{(2 \times 1) - (0 \times 1)}{0.5} = 1$	
s^1		$\frac{(0.5 \times 1) - (1 \times 2)}{0.5} = \frac{-1.5}{0.5} = -3$			
s^0	1				

Step 3 – Verify the sufficient condition for the Routh-Hurwitz stability.

There are two sign changes in the first column of Routh table. Hence, the control system is unstable.

In the Routh-Hurwitz stability criterion, we can know whether the closed loop poles are in on left half of the s plane or on the right half of the s plane or on an imaginary axis. So, we cant find the nature of the control system. To overcome this limitation, there is a technique known as the root locus

