



ROHINI COLLEGE OF ENGINEERING AND TECHNOLOGY

AUTONOMOUS INSTITUTION

Approved by AICTE & Affiliated to Anna University

NBA Accredited for BE (ECE, EEE, MECH) | Accredited by NAAC with A+ Grade

Anjugramam - Kanyakumari Main Road, Palkulam, Variyoor P.O. - 629 401, Kanyakumari District.

CAI 335 : SOLAR AND WIND ENERGY SYSTEMS

UNIT 4

WINDMILL DESIGN AND APPLICATIONS

Prepared by:

Mr.Arunpandian.N.

Assistant Professor

Department of Agricultural Engineering

In a wind energy system, the **transmission, rotors, pumps, and generators** all work together to convert the kinetic energy from the wind into electrical or mechanical energy, which can then be used for various applications. These components play crucial roles in the wind turbine's overall performance, efficiency, and energy output. Below is a detailed explanation of each of these components and their roles in the system.

1. Transmission in Wind Energy System

The **transmission system** in a wind turbine is responsible for transmitting the mechanical power generated by the rotor (blades) to the generator, where it is converted into electrical power. It typically consists of various components, including the gearbox, shaft, and sometimes a generator coupling, which work together to transfer and convert the mechanical energy.

Key Components:

- **Main Shaft:**
 - The main shaft connects the rotor (blades) to the gearbox or generator. The rotor blades' rotational motion is transferred to the shaft, which then transmits the mechanical energy to the gearbox or directly to the generator in some designs.
 - **Low-Speed Shaft:** This is the shaft that connects the rotor to the gearbox. It rotates at a lower speed but with higher torque due to the slower rotational speed of the rotor.
 - **High-Speed Shaft:** This shaft typically connects the gearbox output to the generator. It rotates at a higher speed due to the gearbox increasing the rotational speed from the low-speed shaft.
- **Gearbox** (in most systems):
 - The gearbox is a mechanical device that increases the rotational speed from the low-speed shaft to a high-speed shaft suitable for the generator. Wind turbines operate at low speeds (10-20 RPM), but generators typically need a much higher speed (around 1,500 to 1,800 RPM), and the gearbox ensures that this speed difference is accommodated.
 - **Types of Gearboxes:**
 - **Two-stage Gearbox:** A gearbox with two gears to increase speed.
 - **Planetary Gearbox:** A more compact gearbox where a central gear (sun gear) drives planetary gears, which in turn drive an outer ring gear.
 - In **direct-drive wind turbines**, a gearbox is not used, and the low-speed shaft connects directly to the generator. This type is becoming more common due to its efficiency and reduced maintenance needs.
- **Coupling:**
 - The coupling connects the gearbox or low-speed shaft to the generator. It ensures that mechanical energy flows from the rotor through the gearbox to the generator. The coupling also helps absorb vibrations and misalignments between the shafts.

Function of Transmission:

- The primary function of the transmission system is to increase the rotational speed from the low-speed rotor to the higher speed needed for efficient electricity generation. This system is integral to maintaining the desired power output and ensuring the smooth operation of the turbine.
-

2. Rotors in Wind Energy System

The **rotor** is the part of the wind turbine that converts the kinetic energy of the wind into mechanical energy. It consists of the **blades**, the **hub**, and sometimes a **pitch control system**. The rotor is the most visible part of the wind turbine and plays a key role in its performance.

Key Components of the Rotor:

- **Blades:**
 - The blades of a wind turbine are designed to capture the wind's energy and convert it into rotational motion. Blades are typically made of lightweight yet strong materials like fiberglass or carbon fiber to withstand wind forces and environmental stresses.
 - **Aerodynamics of Blades:** The shape and angle of the blades determine how efficiently they capture wind energy. Most modern turbines use **aerofoil-shaped blades** (similar to an airplane wing) to maximize the amount of energy captured from the wind. The pitch (angle) of the blades can be adjusted to optimize energy capture for varying wind speeds.
- **Hub:**
 - The hub is the central part of the rotor to which the blades are attached. It connects the blades to the shaft and is responsible for transmitting the rotational energy from the blades to the shaft.
 - **Yaw Control:** The hub is typically connected to a yaw system that allows the rotor to face into the wind direction to maximize energy capture.
- **Pitch Control System:**
 - In some turbines, the **pitch control system** adjusts the angle of the blades to regulate the turbine's power output and protect it from high winds. This system changes the blade angle to optimize power capture during varying wind speeds.
 - **Pitching up:** Increasing the angle of the blades reduces the rotational speed and power output to prevent the turbine from producing too much energy during high winds.
 - **Pitching down:** Decreasing the angle increases the blade's efficiency in lower winds.

Function of the Rotor:

- The rotor's primary function is to harness the kinetic energy of the wind and convert it into rotational mechanical energy. The rotational motion generated by the rotor is then transferred to the drivetrain and ultimately to the generator, where it is converted into electrical power.
-

3. Pumps in Wind Energy Systems

While pumps are not always a central feature of all wind energy systems, they can play a role in certain applications, particularly in **hydraulic drive systems** and **cooling systems** for wind turbines.

Hydraulic Drive Systems:

- In some wind turbines, especially **large-scale turbines**, a **hydraulic pump** can be used to transfer power from the rotor to the generator or gearbox.
- **Hydraulic systems** are employed for certain turbine designs to replace traditional mechanical gearboxes. In these systems, a hydraulic motor receives power from the turbine's rotor and turns a pump that drives a hydraulic generator.
- Hydraulic systems can help reduce the mechanical complexity of the turbine by eliminating the need for large gearboxes and direct-drive systems.

Cooling Systems:

- Wind turbines, especially those used in large offshore wind farms, require cooling systems to maintain optimal temperatures for the generator and other electronic components.
- **Coolant pumps** circulate coolant fluids around the generator to prevent overheating, ensuring the turbine operates efficiently and preventing failure due to excessive heat.

Pumping Water (Not Common in Wind Energy, But Related):

- Although not a direct component of wind energy generation, **windmills** have historically been used to pump water, especially in agricultural settings. These wind-driven pumps have been used for centuries to pump water from wells or to irrigate crops.
-

4. Generators in Wind Energy System

The **generator** in a wind turbine is the component responsible for converting the mechanical energy from the rotor into electrical energy. It plays a vital role in the overall energy production of the wind turbine.

Types of Generators:

- **Synchronous Generators:**
 - These generators operate at a fixed speed and produce alternating current (AC). Synchronous generators are more efficient at higher power levels and are typically used in larger wind turbines.
 - They require a **converter** to connect to the grid, since the frequency of the wind turbine's output might not exactly match the grid frequency.
- **Asynchronous (Induction) Generators:**
 - These generators do not require synchronization with the grid frequency. Instead, they generate electricity by induction and can operate at variable speeds, which is suitable for wind energy systems where wind speed varies constantly.
 - They are less efficient than synchronous generators but are simpler and cheaper, often used in smaller-scale or older wind turbines.
- **Permanent Magnet Synchronous Generators (PMSG):**
 - These generators use permanent magnets instead of electromagnets to generate electricity. They are highly efficient and are commonly used in **direct-drive systems** (systems that do not require a gearbox).
 - PMSGs are increasingly popular due to their higher efficiency and reliability, especially in offshore wind farms.

Function of the Generator:

- The generator's function is to convert the mechanical energy of the spinning rotor (transmitted through the transmission system) into electrical energy. The generator produces electricity at variable speeds in most wind turbines, and this electricity is typically passed through a power converter or inverter before being sent to the grid or used locally.

Conclusion:

- **Rotors** are the first stage of energy conversion in a wind turbine, capturing the kinetic energy of the wind.
- The **transmission system** ensures that this mechanical energy is efficiently transferred from the rotor to the generator, often using a gearbox and shaft system.
- **Pumps** in wind energy systems are typically used in hydraulic drive systems or cooling systems, improving efficiency and preventing overheating.

- **Generators** convert the mechanical energy into electrical power, which is either stored or transmitted to the grid for distribution.

Together, these components form the core of a wind energy system, with each element working in harmony to harness wind power and convert it into usable energy. Understanding the role and function of each part is essential for optimizing turbine design and improving the overall performance of wind farms.

In wind energy systems, the way power is generated and distributed can be classified into two main categories: **standalone systems** and **grid-connected systems**. These systems differ in how they store or deliver the electricity generated by the wind turbine. Below is a detailed explanation of each system, how they work, and their advantages and disadvantages.

1. Standalone Wind Energy System

A **standalone wind energy system** (also known as an **off-grid system**) is designed to operate independently of the electricity grid. It is typically used in remote locations where connecting to the grid is not feasible or economical. This system generates and stores energy locally to be used directly by the user, without any reliance on the main grid.

Key Components of a Standalone Wind Energy System:

- **Wind Turbine:** The wind turbine captures the kinetic energy of the wind and converts it into electrical energy. The size and capacity of the turbine depend on the power needs of the system.
- **Battery Storage:** In standalone systems, energy storage is a critical component. **Batteries** (often **deep-cycle batteries** like lead-acid or lithium-ion) store the electricity generated by the wind turbine when the wind is blowing. This stored energy can then be used when the wind isn't blowing or during periods of high demand.
- **Charge Controller:** A **charge controller** is used to manage the flow of electricity from the wind turbine to the battery bank. It ensures that the batteries are charged safely and prevents overcharging or deep discharge, which can shorten the battery's life.
- **Inverter:** Wind turbines generally produce **direct current (DC)** electricity, but most household appliances and devices use **alternating current (AC)**. The **inverter** converts the DC power stored in the batteries into AC power suitable for use in the household or other local applications.
- **Load:** The load is the electrical demand that the system is supplying, such as homes, businesses, or small industrial equipment. In standalone systems, the load is typically small to medium-scale, such as powering homes, remote facilities, or agricultural operations.

Working Principle of Standalone Wind Energy System:

- The wind turbine captures wind energy and converts it into electrical power. When the wind is blowing and the turbine is generating electricity, the power is used to charge the battery bank.
- During periods of low wind or no wind, the batteries provide the necessary power to supply the load.
- The charge controller regulates the flow of electricity to and from the battery, ensuring proper charging and discharging.
- If there is a need for AC power, the inverter converts the stored DC electricity into AC.

Advantages of Standalone Wind Energy System:

- **Independence from the Grid:** It is ideal for remote areas where extending the grid would be too expensive or impractical.
- **Energy Security:** Provides a reliable source of energy without depending on the national or regional grid, ensuring energy security.
- **Environmental Impact:** Clean, renewable energy that reduces reliance on fossil fuels, minimizing the carbon footprint.

Disadvantages of Standalone Wind Energy System:

- **Storage Capacity Limitations:** The system relies on batteries for energy storage, which can limit the amount of power available during periods without wind. Batteries also have a finite lifespan and require maintenance or replacement over time.
- **Higher Initial Cost:** Installing a standalone system with a battery bank, charge controller, and inverter can be expensive upfront, particularly for larger systems.
- **Variable Power Supply:** The power output of the wind turbine is subject to fluctuations in wind speed, which can lead to periods of insufficient energy generation if the wind is calm.
- **Limited Scalability:** Standalone systems are typically suited for small-scale applications, and scaling them up for larger uses can become complex and costly.

2. Grid-Connected Wind Energy System

A **grid-connected wind energy system** (also known as a **grid-tied system**) is designed to operate in conjunction with the electrical grid. This system generates electricity from wind, but the power produced is fed into the utility grid, where it can be distributed and used by consumers. Grid-connected systems are more common in commercial and industrial wind farms, as well as in residential applications where excess energy is supplied to the grid.

Key Components of a Grid-Connected Wind Energy System:

- **Wind Turbine:** As in standalone systems, the wind turbine captures wind energy and converts it into electrical power. This electricity is typically **alternating current (AC)** in grid-connected systems, though some systems might use a generator that produces DC, which is then converted to AC using an inverter.
- **Inverter:** The inverter in a grid-connected system is crucial. It converts the **DC electricity** from the wind turbine (or the generator) into **AC electricity**, which is compatible with the electricity grid. The inverter must synchronize the phase and frequency of the wind-generated electricity with that of the grid.
- **Grid Connection:** The power produced by the wind turbine is fed directly into the **electricity grid**. The wind farm or individual turbine is connected to the grid, allowing it to distribute the electricity to homes, businesses, and other facilities.
- **Metering System:** In a grid-connected system, **net metering** is often used. This system measures the amount of electricity the wind system generates and sends to the grid. If the system produces more power than is consumed locally, the excess is fed into the grid, and the owner may receive credit for this power from the utility company.
- **Protection and Control Systems:** These systems ensure the safety and efficiency of the wind turbine and grid connection. They include systems that protect against overvoltage, under-voltage, or power surges, and help manage the flow of electricity to prevent grid instability.

Working Principle of Grid-Connected Wind Energy System:

- The wind turbine generates electricity from the wind. If the wind turbine produces more electricity than is needed locally, the excess is fed into the electrical grid.
- The inverter ensures that the power fed into the grid matches the required voltage, frequency, and phase to maintain grid stability.
- Grid-connected systems can also draw electricity from the grid if the wind energy produced is insufficient to meet demand, ensuring a constant and reliable power supply.
- With **net metering**, consumers may be credited for excess power sent to the grid, which can reduce their electricity bills or provide compensation for their contribution to the grid.

Advantages of Grid-Connected Wind Energy System:

- **No Need for Energy Storage:** Since the wind energy is fed into the grid, there is no need for expensive battery storage. Power can be drawn from the grid when the turbine is not generating enough electricity.
- **Reliability:** A grid-connected system can provide reliable power because it can draw from the grid when wind conditions are poor.
- **Economic Benefits:** In many cases, the system owner can receive compensation or credits for excess power sent to the grid, which can help offset the cost of the system.
- **Scalability:** Grid-connected systems can be scaled up more easily for larger energy demands, making them ideal for wind farms and large commercial or industrial installations.

Disadvantages of Grid-Connected Wind Energy System:

- **Dependence on the Grid:** Grid-connected systems are still dependent on the electricity grid. If there is a grid failure or blackout, the wind turbine will generally stop operating, unless an additional **backup system** is in place.
 - **Regulatory and Grid Integration Challenges:** Connecting to the grid requires compliance with regulations, and in some regions, there may be bureaucratic hurdles or technical challenges related to grid integration and coordination with the utility company.
 - **Variable Power Generation:** Wind is intermittent and not always reliable. As wind speeds fluctuate, so does the amount of electricity generated. Although grid-connected systems can rely on the grid during calm periods, this variability can impact energy stability if not well-managed.
-

3. Comparison of Standalone and Grid-Connected Wind Energy Systems

| Feature | Standalone Wind Energy System | Grid-Connected Wind Energy System |
|---------------------------|---|---|
| Power Storage | Requires batteries for energy storage | No need for batteries; power is fed directly to the grid |
| Energy Reliability | Dependent on battery storage and wind conditions | Can draw power from the grid when wind energy is insufficient |
| Complexity | More complex due to battery management and power control | Less complex in terms of power management |
| Grid Independence | Completely independent of the electrical grid | Requires connection to the electrical grid |
| Cost | High initial cost due to battery storage, charge controllers, and inverters | Lower maintenance costs but may have installation costs depending on the grid connection |
| Energy Export | Cannot export excess energy; energy is used on-site | Excess energy can be exported to the grid, potentially generating income through net metering |
| Suitability | Ideal for remote or off-grid locations, small-scale power needs | Ideal for larger-scale installations, commercial, or industrial uses |

4. Conclusion

Both **standalone** and **grid-connected** wind energy systems have their unique advantages and are suited for different applications. A **standalone system** is perfect for off-grid locations, offering energy independence and sustainability for small communities or isolated areas. In contrast, a **grid-connected system** is ideal for large-scale installations where the electricity produced can be integrated into the broader power grid, providing an efficient and reliable power supply with the added potential of generating income from excess electricity.

The choice between these two systems depends on the specific needs of the user, including location, energy demand, and whether or not grid connectivity is available.